

- ❖ Polycrystalline Solar Panel : 18V-100W
- ❖ Sealed Lead Acid battery : 12V-50Ah
- ❖ Controller : 12V 15 A
- ❖ Pure Sine Wave Inverter : 12V 300 watt
- ❖ DC Cigar - lighter Socket : 1 pc
- ❖ AC Charger Socket + wire : 1 unit
- ❖ DC Output Socket : 12V - 5pcs
- ❖ 5V USB output socket : 1pcs
- ❖ AC Output 3 Pin 230V Socket : 2pcs
- ❖ LIFE span for the battery about 6-8 years if used according to our specification
- ❖ Load : LED light,65W fan,Labtop, Mobile Charger
- ❖ Battery Charging Time : Approx 8 hours for full Charge
- ❖ Able to Support : 12V 6W LED light 5pcs Works for 12 hours
- ❖ Accessories : Include 10 Meter wire with socket for panel and 5 Meter for light/fan
- ❖ Solar Panel Size : 1016\*670\*30mm
- ❖ Control Tower Size : 390\*270\*410mm
- ❖ Net weight about 45Kg
- ❖ Important : Remember to connect the grounding wire to the given socket at the back of solar generator, This maintenance free equipments life span about 25 to 40 years if only used According to our instruction except the battery and bulb.
- ❖ Never overdraw current supply above 100W at all the time

International Office in Singapore :

55, Siglap rd,  
B1-01 Siglap Centre  
Singapore 455871  
Tel : 938 415 38



## 100 Watt Solar Power Generator

Quality Products can never be Compared with Inferior Products



誰が私たちの高品質の製品に対抗することができますか？



Highest in the Whole World

